

Product Detail:

Code: C00408

Model: BOOSTER 3100-6100

PROFESSIONAL PORTABLE START BOOSTER AND RECHARGEABLE POWER SOURCE

It's ideal for any application where a portable powerful quick-start or/and a long lasting power source is needed.

Designed for operating mostly at 12V and occasionally at 24V, it can be used as:

- An emergency starter.
- An additional power source for vehicles (memory saver).
- A multipurpose additional power source (for electrical 12V or 24V devices).

It is rechargeable by connecting it to the cigarette lighter of the vehicle or to the electricity network.

It can be stored in any position without risking acid leakage.

It comes with protection fuses against short-circuits, a 20 amps automatic reset breaker, protection circuits against peak tensions to protect the vehicle electronic system and with charge test button with LEDS.

It delivers at 12V a starting current of 6000 amps and at 24V a starting current of 3000 amps. It delivers a minimum of 1150 constant amps.

Including, as standard: power supply LESA 8, cigarette lighter charger cable LESA1, clamps with 6-wire copper cable.



Technical Data:

Code	C00408
Item	BOOSTER 3100/6100
Supply voltage (single phase)	230 V
Voltage	12 V 24 V
Peak current output	3000 / 6000 A p
Constant current output	1150 A
Charge voltage	max 14,9 V
Recharge voltage	12V 4Ah
Automatic power supply	LESA 8
Charging cable 12V	LESA 1
Insulated clamps	YES
Sealed and maintenance free battery	2 x 23Ah
Overload protection	YES
Number of batteries	2
Weight	20 kg
Dimensions	410x175x310h mm
Cable length	1550 mm
Cables section	50 mm ²

Accessories:


LESA1

LESA1



372536

LESA8