Elettro C.F. s.r.l.
via Miglioli, 24 40024 - Castel San Pietro Terme (Bologna) Italy
Telefono +39 051941453 - +39 0516942026 - FAX +39 051944602
C.F. e Registro Imprese BO n. 00706680378 - P.I. 00521381202 - Capitale Sociale 72.320,00 i.v.

Les détails du produit:

Code: C00406 **Modèle:**BOOSTER 3100



PROFESSIONAL PORTABLE START BOOSTER AND RECHARGEABLE POWER SOURCE

It's ideal for any application where a portable powerful quick-start or/and a long lasting power source is needed. It can be used as:
•An emergency starter.
•An additional power source for vehicles (memory saver).
•A multipurpose additional power source (for electrical 12V devices).
It is rechargeable by connecting it to the cigarette lighter of the vehicle or to the electricity network.
It can be stored in any position without risking acid leakage.
It comes with a 20 amps automatic reset breaker, with protection circuits against peak tensions to protect the vehicle electronic system and with charge test button with LEDS.
It delivers 3100 peak amps and a minimum of 1150 constant amps.

Including, as standard: power supply LESA 6A, cigarette lighter charger cable LESA1, clamps with 6-wire copper cable, black clamp with LED.

Elettro C.F. s.r.l.
via Miglioli, 24 40024 - Castel San Pietro Terme (Bologna) Italy
Telefono +39 051941453 - +39 0516942026 - FAX +39 051944602
C.F. e Registro Imprese BO n. 00706680378 - P.I. 00521381202 - Capitale Sociale 72.320,00 i.v.

Fiche technique:

Code	C00406
Item	BOOSTER 3100
Supply voltage (single phase)	230 V
Voltage	12 V
Peak current output	3100 A p
Constant current output	1150 A
Charge voltage	max 14,9 V
Recharge voltage	12V 1,5 Ah
Automatic power supply	LESA 6A
Charging cable 12V	LESA 1
Insulated clamps	YES
Sealed and maintenance free battery	12V 23Ah
Overload protection	YES
Number of batteries	1
Weight	12 kg
Dimensions	410x135x310h mm
Cable length	1550 mm
Cables section	25 mm2

Accessoires:

 LESA1 LESA1

 372535 LESA6A