Elettro C.F. s.r.l.
via Miglioli, 24 40024 - Castel San Pietro Terme (Bologna) Italy
Telefono +39 051941453 - +39 0516942026 - FAX +39 051944602
C.F. e Registro Imprese BO n. 00706680378 - P.I. 00521381202 - Capitale Sociale 72.320,00 i.v.

Les détails du produit:

Code: C00400 **Modèle:**BOOSTER 1800



PROFESSIONAL PORTABLE START BOOSTER AND RECHARGEABLE POWER SOURCE

It's ideal for any application where a portable powerful quick-start or/and a long lasting power source is needed. It can be used as:
•An emergency starter.
•An additional power source for vehicles (memory saver).
•A multipurpose additional power source (for electrical 12V devices).
•Suitable for frequent use.
•Suitable for vehicles with battery up to 100Ah.

It is rechargeable by connecting it to the cigarette lighter of the vehicle or to the electricity network.
It can be stored in any position without risking acid leakage.
It comes with a 20 amps automatic reset breaker, with protection circuits against peak tensions to protect the vehicle electronic system and with charge test button with LEDS.
It delivers 1800 peak amps and a minimum of 600 constant amps.

Including, as standard: power supply LESA 6A, cigarette lighter charger cable LESA1 with LEDs, curved and highly adherent clips with 6-wire copper cable.

Elettro C.F. s.r.l.
via Miglioli, 24 40024 - Castel San Pietro Terme (Bologna) Italy
Telefono +39 051941453 - +39 0516942026 - FAX +39 051944602
C.F. e Registro Imprese BO n. 00706680378 - P.I. 00521381202 - Capitale Sociale 72.320,00 i.v.

Fiche technique:

Code	C00400
Item	BOOSTER 1800
Supply voltage (single phase)	230 V
Voltage	12 V
Peak current output	1800 A p
Constant current output	600 A
Charge voltage	max 14,9 V
Recharge voltage	12V 1,5 Ah
Automatic power supply	LESA 6A
Charging cable 12V	LESA 1
Insulated clamps	YES
Sealed and maintenance free battery	12V 18pro Ah
Overload protection	YES
Number of batteries	1
Weight	8,8 kg
Dimensions	325x110x285h mm
Cable length	870 mm
Cables section	25 mm2

Accessoires:



LESA1 LESA1



372535 LESA6A