

Produktdetail:

Code: C00403

Vorlage:BOOSTER 2500

PORTABLE BOOST STARTER AND RECHARGEABLE POWER SUPPLY SOURCE

It is ideal for any application where a portable powerful quick-start or/and a long lasting power source is needed. It can be used as:

- A battery charger (12V).
- An emergency starter.
- An additional power source for vehicles (memory saver).
- A multipurpose additional power source (for electrical 12V devices).

It is rechargeable by plugging the power supply LESA 6A into any 230V household outlet or by plugging the charging cable LESA1 into the cigarette lighter of the vehicle.

It can be stored in any position without risking acid leakage.

It comes with a 20 amps automatic reset breaker, with protection circuits against peak tensions to protect the vehicle electronic system and with charge test button with LEDs.

It delivers 2500 peak amps and a minimum of 950 constant amps.

Including, as standard: power supply LESA 6A, cigarette lighter charger cable LESA1, heavy-duty clamps with 6-wire copper cable.



Datenblatt:

| | |
|-------------------------------------|----------------------|
| Code | C00403 |
| Item | BOOSTER 2500 |
| Supply voltage (single phase) | 230 V |
| Voltage | 12 V |
| Peak current output | 2500 A |
| Constant current output | 950 A |
| Charge voltage | max 14,9 V |
| Recharge voltage | LESA 6A (12V 1,5 Ah) |
| Automatic power supply | YES |
| Charging cable 12V | LESA 1 |
| Insulated clamps | YES |
| Sealed and maintenance free battery | 12V 26Ah |
| Overload protection | YES |
| Number of batteries | 1 |
| Weight | 10,5 kg |
| Dimensions | 370x125x300h mm |
| Cable length | 1550 mm |
| Cables section | 40 mm |

Zubehör: