Elettro C.F. s.r.l.
via Miglioli, 24 40024 - Castel San Pietro Terme (Bologna) Italy
Telefono +39 051941453 - +39 0516942026 - FAX +39 051944602
C.F. e Registro Imprese BO n. 00706680378 - P.I. 00521381202 - Capitale Sociale 72.320,00 i.v.

Les détails du produit:

Code: C00403 **Modèle:**BOOSTER 2500



PORTABLE BOOST STARTER AND RECHARGEABLE POWER SUPPLY SOURCE

It is ideal for any application where a portable powerful quick-start or/and a long lasting power source is needed. It can be used as:
•A battery charger (12V).
•An emergency starter.
•An additional power source for vehicles (memory saver).
•A multipurpose additional power source (for electrical 12V devices).
It is rechargeable by plugging the power supply LESA 6A into any 230V household outlet or by plugging the charging cable LESA1 into the cigarette lighter of the vehicle.
It can be stored in any position without risking acid leakage.
It comes with a 20 amps automatic reset breaker, with protection circuits against peak tensions to protect the vehicle electronic system and with charge test button with LEDS.
It delivers 2500 peak amps and a minimum of 950 constant amps.

Including, as standard: power supply LESA 6A, cigarette lighter charger cable LESA1, heavy-duty clamps with 6-wire copper cable.

Elettro C.F. s.r.l.
via Miglioli, 24 40024 - Castel San Pietro Terme (Bologna) Italy
Telefono +39 051941453 - +39 0516942026 - FAX +39 051944602
C.F. e Registro Imprese BO n. 00706680378 - P.I. 00521381202 - Capitale Sociale 72.320,00 i.v.

Fiche technique:

Code	C00403
Item	BOOSTER 2500
Supply voltage (single phase)	230 V
Voltage	12 V
Peak current output	2500 A
Constant current output	950 A
Charge voltage	max 14,9 V
Recharge voltage	LESA 6A (12V 1,5 Ah)
Automatic power supply	YES
Charging cable 12V	LESA 1
Insulated clamps	YES
Sealed and maintenance free battery	12V 26Ah
Overload protection	YES
Number of batteries	1
Weight	10,5 kg
Dimensions	370x125x300h mm
Cable length	1550 mm
Cables section	40 mm

Accessoires: