

## Les détails du produit:

**Code:** C00407

**Modèle:** BOOSTER 3200

### PORTABLE BOOST STARTER AND RECHARGEABLE POWER SUPPLY SOURCE

It is ideal for any application where a portable powerful quick-start or/and a long lasting power source is needed.

It's indicated for a high number of starts even if very intensive and doesn't need to be recharged frequently.

It's recommended for coaches, road haulage fleets and vehicles with particular difficulties in charge.

It can be used as:

- A battery charger (24V).
- An emergency starter.
- An additional power source for vehicles (memory saver).
- A multipurpose additional power source (for electrical 24V devices).

It can be powered by connection to the mains electrical supply.

It can be stored in any position without the risk of acid leakage.

It comes with a 20 amps automatic thermal protection, with protection circuits against peak tensions to protect the vehicle electronic system and with charge test button.

It delivers 3200 peak amps and a minimum of 900 constant amps.

Including, as standard: power supply LESA 7A, heavy-duty clamps with 6-wire copper cable.



**Fiche technique:**

Code	C00407
Item	BOOSTER 3200
Supply voltage (single phase)	230 V
Voltage	24 V
Peak current output	3200 A
Constant current output	900 A
Charge voltage	max 25,2 V
Recharge voltage	LESA 7A (24V 2Ah)
Automatic power supply	YES
Charging cable 12V	NO
Insulated clamps	YES
Sealed and maintenance free battery	12V 26Ah
Overload protection	YES
Number of batteries	2
Weight	26,5 kg
Dimensions	240x380x680h mm
Cable length	1550 mm
Cables section	40 mm

**Accessoires:**