

Detalle del producto:

Código: C00400

Modelo: BOOSTER 1800

PROFESSIONAL PORTABLE START BOOSTER AND RECHARGEABLE POWER SOURCE

It's ideal for any application where a portable powerful quick-start or/and a long lasting power source is needed. It can be used as:

- An emergency starter.
- An additional power source for vehicles (memory saver).
- A multipurpose additional power source (for electrical 12V devices).
- Suitable for frequent use.
- Suitable for vehicles with battery up to 100Ah.

It is rechargeable by connecting it to the cigarette lighter of the vehicle or to the electricity network.

It can be stored in any position without risking acid leakage.

It comes with a 20 amps automatic reset breaker, with protection circuits against peak tensions to protect the vehicle electronic system and with charge test button with LEDs.

It delivers 1800 peak amps and a minimum of 600 constant amps.

Including, as standard: power supply LESA 6A, cigarette lighter charger cable LESA1 with LEDs, curved and highly adherent clips with 6-wire copper cable.



Ficha de datos:

| | |
|-------------------------------------|--------------------|
| Code | C00400 |
| Item | BOOSTER 1800 |
| Supply voltage (single phase) | 230 V |
| Voltage | 12 V |
| Peak current output | 1800 A p |
| Constant current output | 600 A |
| Charge voltage | max 14,9 V |
| Recharge voltage | 12V 1,5 Ah |
| Automatic power supply | LESA 6A |
| Charging cable 12V | LESA 1 |
| Insulated clamps | YES |
| Sealed and maintenance free battery | 12V 18pro Ah |
| Overload protection | YES |
| Number of batteries | 1 |
| Weight | 8,8 kg |
| Dimensions | 325x110x285h mm |
| Cable length | 870 mm |
| Cables section | 25 mm ² |

Accesorios:


LESA1

LESA1



372535

LESA6A