**Elettro C.F. s.r.l.**
via Miglioli, 24 40024 - Castel San Pietro Terme (Bologna) Italy
Telefono +39 051941453 - +39 0516942026 - FAX +39 051944602
C.F. e Registro Imprese BO n. 00706680378 - P.I. 00521381202 - Capitale Sociale 72.320,00 i.v.

# Les détails du produit:

**Code:** C00598 **Modèle:**START 650




THREE-PHASE WHEEL MOUNTED BATTERY CHARGERS WITH QUICK STARTER

-Suitable for all types of lead batteries.
-Provided with automatic protection against overload and polarity reversals.
-Supplied with cables and clips.
-Equipped with remote control.
-Provided with rapid charge with timer.

Different voltages available on request

## Fiche technique:

| | |
|---|---|
| Code | C00598 |
| Item | START 650 |
| Input Voltage | 3x230/400V 50/60 Hz |
| Charge voltage | 12-24V |
| Charge/start current eff. | 50 / 650 A |
| Charge adjustments | n. 4 |
| Installation power | 6 kW |
| Conventional charge current arithm EN 60335-2-29 | 20A - 50A |
| Conventional start current arithm EN 60335-2-29 | 330 A (12V) 360 A (24V) |
| Dimensions | mm 280x370x680h |
| Weight | 30 kg |

**Elettro C.F. s.r.l.**
via Miglioli, 24 40024 - Castel San Pietro Terme (Bologna) Italy
Telefono +39 051941453 - +39 0516942026 - FAX +39 051944602
C.F. e Registro Imprese BO n. 00706680378 - P.I. 00521381202 - Capitale Sociale 72.320,00 i.v.

## Accessoires: