

Produktdetail:

Code: C00592

Vorlage: START 800

THREE-PHASE WHEEL MOUNTED BATTERY CHARGERS WITH QUICK STARTER

- Suitable for all types of lead batteries.
- Provided with automatic protection against overload and polarity reversals.
- Supplied with cables and clips.
- Equipped with remote control.
- Provided with rapid charge with timer.

Different voltages available on request



Datenblatt:

Code	C00592
Item	START 800
Input Voltage	3x230/400V 50/60 Hz
Charge voltage	12-24 V
Charge/start current eff.	120 / 800 A
Charge adjustments	n. 6
Installation power	13 kW
Conventional charge current arithm EN 60335-2-29	80A (12V) – 100A (24V)
Conventional start current arithm EN 60335-2-29	580 A (12V) 700 A (24V)
Dimensions	mm 360x500x850h
Weight	62 kg



Elettro C.F. s.r.l.

via Miglioli, 24 40024 - Castel San Pietro Terme (Bologna) Italy

Telefono +39 051941453 - +39 0516942026 - FAX +39 051944602

C.F. e Registro Imprese BO n. 00706680378 - P.I. 00521381202 - Capitale Sociale 72.320,00 i.v.

Zubehör: