Elettro C.F. s.r.l.
via Miglioli, 24 40024 - Castel San Pietro Terme (Bologna) Italy
Telefono +39 051941453 - +39 0516942026 - FAX +39 051944602
C.F. e Registro Imprese BO n. 00706680378 - P.I. 00521381202 - Capitale Sociale 72.320,00 i.v.

Les détails du produit:

Code: C00593 **Modèle:**START 1200



THREE-PHASE WHEEL MOUNTED BATTERY CHARGERS WITH QUICK STARTER

-Suitable for all types of lead batteries.
-Provided with automatic protection against overload and polarity reversals.
-Supplied with cables and clips.
-Equipped with remote control.
-Provided with rapid charge with timer.

Different voltages available on request

Fiche technique:

Code	C00593
Item	START 1200
Input Voltage	3x230/400V 50/60 Hz
Charge voltage	12-24V
Charge/start current eff.	120 / 1200 A
Charge adjustments	n. 6
Installation power	19 kW
Conventional charge current arithm EN 60335-2-29	80A (12V) – 100A (24V)
Conventional start current arithm EN 60335-2-29	920A (12V) 1100A (24V)
Dimensions	mm 360x500x850h
Weight	74 kg

Elettro C.F. s.r.l.
via Miglioli, 24 40024 - Castel San Pietro Terme (Bologna) Italy
Telefono +39 051941453 - +39 0516942026 - FAX +39 051944602
C.F. e Registro Imprese BO n. 00706680378 - P.I. 00521381202 - Capitale Sociale 72.320,00 i.v.

Accessoires: